

Ficha técnica

Brother

Modelos / familias

PT-D460BT

Fuente del fabricante

User's Guide (HTML/PDF)

<https://support.brother.com/g/s/es/htmldoc/ptouch/d410/uken/PDF/PDF.pdf>

Las páginas siguientes son un extracto técnico del documento oficial del fabricante.

Specifications

- >> [Printing](#)
- >> [Size](#)
- >> [Interface](#)
- >> [Environment](#)
- >> [Power Supply](#)
- >> [Media](#)
- >> [Memory](#)
- >> [Compatible Operating Systems](#)

Printing

Print Speed (Depending on the media used)	Maximum 20 mm/s (PT-D410) Maximum 30 mm/s (PT-D460BT)
Maximum Print Height	15.8 mm (when using 18 mm tape) ¹

¹ The actual character size may be smaller than the maximum print height.

Size

Weight	Approximately 760 g (without batteries and Tape Cassette) (PT-D410) Approximately 770 g (without batteries and Tape Cassette) (PT-D460BT)
Dimensions	Approximately 187 mm (W) x 178 mm (D) x 72 mm (H) (PT-D410) Approximately 187 mm (W) x 178 mm (D) x 72 mm (H) (PT-D460BT)
LCD	128 dot x 48 dot (PT-D410) 320 dot x 120 dot (PT-D460BT)

Interface

USB	USB Ver.2.0 (Full Speed) (Micro B)
Bluetooth (PT-D460BT)	Bluetooth Ver.5.0 SPP: iAP2

Environment

Operating Temperature	Between 10°C and 35°C
Operating Humidity	Between 20% and 80% Maximum wet bulb temperature: 27°C

Power Supply

Battery	Six AA alkaline batteries (LR6) AC Adapter (AD-E001A)
----------------	--

Media

Tape Width	Standard TZe Tape Cassette: 3.5 mm, 6 mm, 9 mm, 12 mm, 18 mm
No. of Lines	18 mm tape: 1 - 5 lines 12 mm tape: 1 - 3 lines 9 mm tape: 1 - 2 lines

	6 mm tape: 1 - 2 lines 3.5 mm tape: 1 line
--	---

Memory

Text Buffer	Maximum 280 characters
File Storage	Maximum 50 files (PT-D410) Maximum 70 files (PT-D460BT)

Compatible Operating Systems

For the latest list of compatible software, visit support.brother.com.



Related Information

- [Appendix](#)

Brother Help and Customer Support

If you need help with using your Brother product, visit support.brother.com for FAQs and troubleshooting tips. You can also download the latest software, drivers and firmware, to improve the performance of your machine, and user documentation, to learn how to get the most from your Brother product.

Further product and support information is available from your local Brother office website. Visit www.brother.com to find the contact details for your local Brother office and to register your new product.



Related Information

- [Appendix](#)
-

brother